

Firmware Release Note



Model : SL-M3370FD, M3375FD, M3870FD, M3870W, SL-M3870FW, M3875FD, M3875FW, M4070FR, SL-M4072FD, M4075FR, M4072FD, M3875HD,	Date :	February 11, 2016
---	--------	-------------------

Version	Category	Change Description
V4.00.01.16 (26-Mar, 2014)	Fix Defect	Fixed the copy fail issue.
	Fix Defect	Easy Printer Manager doesn't update downloaded font list when multi font download using PJI
V4.00.01.27 (23-Dec, 2014)	Add Func.	Add a new error code (M3-1112, Jam Inside of Machine)
	Fix Defect	OTG cable compatibility
		Remove unused Network Port such as TCP 22 port.
		Can not upload CA certification from SyncThru Web Service.
V4.00.01.28 (4-Feb, 2015)	Add Func.	Fix Google Cloud Print issues.
		Apply to Samsung Cloud Print Function.
V4.00.01.30 (5-Oct, 2015)	Add Func.	Apply to Toner Status and Easy setup of Samsung Cloud Print
		Apply the new font in PCL5, PCL6, Postscript
		Support for SPDS Android App.(for repair service)
		Support Proxy Server Authentication
		Scan to SMB/FTP maximum users should be increased from 20 to 200
	Fix Defect	GCP print & deregistration doesn't work properly
		Google Cloud print with proxy connection is not working as expected
		occur memory leak when GCP confirm popup is displayed on LUI
		Time Zone is not getting Applied and Changed in DST.
		[SWAS Job Accounting] Device didn't send a reponse to SWAS
		[SyncThruAccount][NoHDD] Missing the job record count when many jobs are running
		Russia summer time issue
		Toner replacement alert is displayed in UI even when part replacement alert is made OFF in Tech Mode.
V4.00.01.32 (11-Feb, 2016)	Fix Defect	Two function for Israel GOV Tender were missing from F/W V4.00.01.29. - Need Email & SMB scan with shortcut. - "Speed dial" do not work when "Prefix dial" set
	Fix Defect	Can not able to proceed the scan to SMB job on touch panel of machine

※ Note

- Please do not turn off the printer and your computer until firmware update finishes.
 - If you are using USB connection, disconnect all other USB printers from the PC.
 - The firmware update you are about to install has been tested for compatibility with Samsung toner cartridge products ONLY.
- Installing The upgrade may cause a non-Samsung toner cartridge to malfunction.
- Do not run your printer during the firmware update.(Do not have any print job)

How to update the firmware using a USB cable.


1. Make sure that the machine is connected to the PC with a USB cable.
2. Set the firmware upgrade 'ON' in the tech mode.

To enter the Tech Mode, press “ Menu, #, 1, 9, 3, 4 ” in sequence

Set the firmware upgrade 'on' in service function

3. Drag the firmware file(*.hd) and Drop down it on usblist2.exe.

And then, firmware update will be started automatically.



4. The firmware update will start.

Once the firmware update is complete, the machine will be rebooted automatically.

Updating from the Network

1. Go to the SyncThruWeb Service (SWS) main home page.

Login as Admin in SyncThruWeb Service.

NOTE: Login using the Administrator ID and Password established during initial machine setup.

2. Click [Maintenance] on the top menu.

And then click [Firmware Upgrade] or Application Management > Application

3. Click Add button
4. Click [Browse]. Choose installation file by browsing file system. And click OK button
5. The uploading step will start. After this step, next step will be started automatically.
6. The firmware update will start.
7. Once the f/w update is complete, the machine power-off and power-on automatically.